

5

AUDIO SURROUND SOUND POWER MANAGEMENT SWITCHING

The invention relates to an audio reproduction system. In particular, the invention relates to an audio system that is switchable between modes in which more or fewer audio amplifiers are selectively activated, for example, for switching between a stereo mode and a surround sound mode.

Background

Switching amplifiers between alternative supply voltages is known to be useful in some situations, and it is of course advantageous to switch off a supply voltage to elements that are unused, so as to avoid unnecessary power dissipation and heat. The SGS Thomson Microelectronics TDA 7294 Class G power amplifier, for example, is specified for dual bipolar supply voltages. Relatively lower magnitude positive and negative supply voltages are normally coupled to the power output stages of the amplifier. When the amplitude of the input voltage exceeds a threshold, higher magnitude supply voltages are switched in automatically, in place of the lower magnitude voltages. This accommodates the necessary swing in the output voltage of the amplifier without clipping, and reduces the average power dissipation of the amplifier because there is a lower voltage drop across the output transistors for a given output current at lower amplitudes, and less power consumption than would be the case at the higher magnitude supply voltages. Effectively, the TDA 7294 amplifier has two different power ratings, and automatically adjusts between the two ratings.

Home entertainment systems are known in which multiple audio outputs are provided to drive speakers that may have several modes of operation. A monaural audio signal requires one speaker; a stereo signal has two speakers that are usually spaced laterally and placed in front of the viewer or other audience; and, a surround-sound arrangement has at least a pair of speakers spaced laterally in front of the audience and a second pair spaced laterally behind the audience. The audio signals to these speakers are driven by signals that differ, sometimes in subtle ways, using combinations of channel separation, phasing and echo to provide a listening experience that can realistically mimic attendance of a performance in an auditorium or such other effect as desired by the program provider.

In order to be capable of presenting a surround sound signal, the entertainment system needs audio amplifiers and speakers for each of the speaker positions in the respective mode. Typically, there are at least five channels, amplifiers and speakers including a left-front, right-front, center-front, left-rear and right-rear.

5 Not all programming contains a surround sound signal. The user may choose to operate in a stereo mode or a monaural mode even if the programming is capable of stereo or surround sound, for example if the necessary speakers and wiring have not been installed. Preferably the system is switchable between these modes.

10 Usually, entertainment systems such as home-theater systems now available, at least have built-in stereo power amplifiers and speakers mounted in their cases. Systems capable of surround sound have additional built-in audio power amplifiers and connector couplings for driving external speakers. The amplifiers and speakers can support the external left-rear and right-rear surround
15 speakers for use with the internal front speakers, or the user may choose instead to use external speakers to carry the left-front, right-front and center-front channel signals in addition to the necessarily external rear speakers. This requires a number of audio amplifiers.

20 Advantageously, menu selections or the like permit the user to configure the system to reflect the mode(s) of operation used. For example, the user may be permitted to disable the surround sound function if no rear speakers have been installed.

25 It is generally accepted in the audio art that for optimum system performance, the average power output of each active channel of a multi-channel system should be equal. If the audio output level applied to each channel or speaker is also equal, then switching from a mode using fewer channels and speakers to a mode using more channels and more speakers effectively multiplies the acoustic output power emitted into the room. Typically the user menu selections or other controls permit multiple axis volume and balance adjustments applicable to one or another of the modes of operation
30 (e.g., left/right balance and front/rear fade). It is also possible that the amplitude of the input signals to the respective amplifiers can be switched automatically when changing modes.

35 There are several needs that are addressed by a system as described, including the capability of switching between modes using more or fewer speakers and the adjustment of the output volume when changing between modes. What such systems fail to provide, however, is an efficient technique for managing power dissipation when switching between modes. Conventional systems wastefully supply power to audio power amplifiers that may be wholly unused in certain modes of
40 operation, and/or supply the same power supply and biasing levels to the amplifiers in each of the modes regardless of differences in the need for output power as a function of the selected mode. An inventive solution is provided for an audio system with multiple amplifiers, each with power supply inputs and audio inputs and outputs, for driving audio speakers according to a selected one of at least two modes of

operation in which a selection of the audio speakers and/or a required power output of the audio speakers differ between the modes. The invention is operable, for example, to an entertainment system that has internal and external speakers and associated amplifiers for switching between stereo and surround sound modes. At least two distinct power supply voltage sources are provided for the amplifiers, and a switching element operates upon switching between the modes to couple one or another of the distinct power supply voltage sources to the power supply inputs of respective ones of the at least two amplifiers. Preferably, the switching element decouples all voltage sources from amplifiers that are unused in one or more modes. This reduces or eliminates power dissipation by the amplifiers, and effectively adjusts the output levels of the amplifiers so that the total audio output of the system is not multiplied, for example, when switching from two stereo outputs to five surround sound outputs. The invention can be switched or can respond to user selections or other reasons to accommodate a particular mode, and can be used to decouple power from amplifiers for unused internal or external speakers.

According to one inventive aspect, an audio system as described is provided with alternative power supply levels for the respective amplifiers used in the respective audio modes. By switching the input voltage to the amplifiers, the output amplitude of the respective channels is adjusted, thereby reducing or eliminating the need for supporting volume level adjustments specific to each mode. The system preferably has the same total audio output power in a stereo mode using internal speakers as in a stereo mode using external speakers, and also has the same total audio output power in a surround sound mode using five speakers. When switching to a mode that does not use a particular channel, this same amplifier power voltage switching technique eliminates power consumption by the power amplifiers of the de-selected channel(s).

Summary

An audio reproduction apparatus, embodying an aspect of the invention, includes a plurality of audio amplifiers, each being responsive to a corresponding audio signal for generating audio power in a corresponding audio speaker. A supply voltage is applied to a first audio amplifier of the audio amplifiers at a lower magnitude, in a first mode of operation, when audio power generated in a second audio amplifier of the audio amplifiers is higher. The supply voltage is at a higher magnitude, in a second mode of operation, when the audio power is generated in the second audio amplifier is lower, in a manner to reduce a change in a total audio power generated, when a change in the mode of operation occurs.

IN THE FIGURES

Figure 1 is a physical layout of an entertainment system or the like according to the invention, with multiple audio modes that selectively employ different combinations of audio speakers;

Figure 2 is a schematic illustration of power supply switching arrangements according to an aspect of the invention; and

Figure 3 is a detailed schematic diagram illustrating a practical embodiment of the invention as generally illustrated in Figure 2.

DETAILED DESCRIPTION

Referring to Figure 1, an exemplary home entertainment system 20 is generally provided in a cabinet 22 having built-in audio speakers, such as a center speaker 26 and left and right stereo speakers 24, 25. The entertainment system 20 preferably includes the capacity to drive additional speakers 32, 42 external to cabinet 22. For a surround sound audio mode, the cabinet speakers 24, 25 (and optionally 26) are supplemented by rear speakers 32 to be disposed behind the area 40 usually occupied by the user or audience. Preferably the user has the option of likewise using external front speakers 27, 28 that either supplement or are used in lieu of the speakers 24, 25 provided in cabinet 22.

The speakers provided in the entertainment system are generally grouped by left versus right and front versus rear categories, and are subject to controls (not shown) that permit the speaker outputs to be balanced at the user's preference. Typically, a balance control varies the output level of the left speakers versus the right speakers. A fader control can similarly vary the output of the front speakers versus the rear speakers. In combination, the speakers can operate, for example, in a monaural mode using only the center speaker 26 or both left and right cabinet speakers 24, 25 together (or perhaps any group of speakers driven from the same signal), or in a stereo mode using one or more pairs of left and right speakers using separated channel signals.

In a preferred embodiment, monaural programming is routed to the left and right cabinet speakers 24, 25, which in that mode present the same signal. Stereo is presented using the left and right front external speakers 27, 28. In a surround sound mode, the speakers are nominally driven with five separated channel signals, namely right front, left front, center front, right rear and left rear, the latter two being routed to rear external speakers 32. In surround sound mode, the rear speakers 32 may be driven from additional separated left and right rear channel signals contained in the program received or being played back by entertainment system 20. Alternatively, the rear speakers 32 may be driven by signals that are the result of processing the separated left and right stereo signals that are coupled to the front speakers 27, 28. In that case, phasing and delay or echo effects may be included so as to provide the sensation of an audio

5 source situated in the area of the front speakers 42, but presented in an auditorium or large space wherein acoustic paths would cause phasing and echo effects similar to those provided as a result of the processing.

10 All of the speakers are driven from the outputs of audio amplifiers 52, 54, 56, shown generally in Figure 2. The audio amplifiers are likewise grouped in pairs, but each channel has a potentially separate signal and in that case requires a separate amplifier or channel. The amplifiers 52, 54, 56 preferably are power or output amplifiers that drive the speakers, although the invention also may be applied to controlling the amplitude of an amplifier stage that is placed upstream of the output amplifiers in a cascaded arrangement. Amplifiers 52, 54, 56 in the
15 embodiment shown can be, for example, SGS Thomson Microelectronics model TDA7265 or equivalent. Audio power amplifiers often can be run on bipolar supply voltages, or they can be unipolar as in the embodiment shown in the drawings. To adapt the invention to a bipolar supply arrangement, the single-sided arrangement shown can be provided with substantially mirror image
20 switching arrangements to change the supply voltages on both the negative and positive supplies when switched.

Gain controls (not shown) are provided in known manner for volume, balance and fade, and enable the user to set a volume level and to balance the relative volume levels laterally and from front to rear. The gain controls can
25 include manually operated control elements such as potentiometers or the like, or can be associated with a system controller, shown generally as an audio source, that adjusts the levels in response to user selections made in a menu technique via an infrared remote control signaling unit or the like, and routes the required signals to the required amplifiers by a switching matrix that in Figure 2 is
30 represented generally by a signal bus. Such user selections can also be the basis for generation of the signal that switches the circuit of the invention between its stereo and surround sound modes.

According to the invention, the audio system has at least amplifiers 52, 54, 56 that each have a power supply input. In the embodiment shown, the
35 left and right amplifiers are in pairs (surround pair, front pair, rear pair) having a single power supply input to each dual amplifier package. Each channel of each of the pairs (i.e., each amplifier) has an audio signal input and audio signal output for driving a speaker. The amplifiers for the speakers 24, 25 permanently mounted in the cabinet (the "internal" speakers) are directly
40 coupled to the respective audio signals as shown in Figure 2. The remaining amplifiers 54, 56 in the embodiment shown are separately coupleable to external speakers 27, 28, 32 by suitable connectors. The amplifiers 52, 54, 56 drive their associated audio speakers to provide an audio power output level

5 that is a function of the gain of each amplifier and the amplitude of the input signal coupled to the amplifier.

The audio system has at least two modes of operation in which one or both of the selection of which audio speakers are to be operational, and the selection of the required power output of the audio speakers, differ between the
10 modes. The required power output of the amplifiers, and thus of the audio speakers is in part a function of the supply voltage coupled to the amplifiers.

According to an inventive aspect, at least two distinct power supply voltage sources are provided for at least certain of the amplifiers. In the embodiment shown, the power supply voltage to a surround sound amplifier
15 package 52 for driving the external rear speakers, is set and unchangeable at a predetermined voltage V_{cc} . This voltage preferably is only applied in the surround sound mode and is not applied in other modes or if the entire unit is turned off and unpowered. The voltages applied to the amplifier 54 for the internal or main left and right speakers (the cabinet speakers) and the voltages
20 applied to the amplifier 56 for the external front left and right speakers, are changeable. Specifically, two different supply voltages V_1 or V_2 , and V_3 or V_4 , respectively, are provided and at least one switching element 62 is operable responsive to a control 64 upon switching between the modes to couple one of the distinct power supply voltage sources to the power supply inputs of the
25 respective amplifier or pair of amplifiers. The switching element 62 can be operable in at least one of the modes of the system to decouple all voltage sources from at least one of the amplifiers, thereby eliminating power dissipation by that amplifier. According to an alternative embodiment, more and fewer amplifiers and speakers can be activated in at least two modes and perhaps
30 additional modes. Figure 3 illustrates the audio amplifiers and their switched power supply arrangements of the entertainment system 20 and power supply - amplifier - speaker arrangements shown in Figures 1 and 2. Similar symbols and numerals in Figures 1, 2 and 3 indicate similar items or functions.

According to the exemplary embodiment shown in Figures 2 and 3, the
35 modes comprise monaural, stereo and surround sound modes of operation. The modes can optionally include one or more modes entered by a setup procedure in which the user selects an option from a menu indicating that no external speakers are coupled to one or the other of the external speaker inputs, in which event the voltage supply to the corresponding amplifier can be switched off.
40 That mode may be useful, for example, to permit the user to choose at his option to employ the surround sound mode but to do so using the internal (cabinet) main left and right speakers 24, 25 (and perhaps a center cabinet

5 speaker 26), for the front speakers used, and external speakers 32 for the rear speakers.

10 The switching element or elements are operable to couple the amplifiers to lower power supply voltages in at least one such mode in which relatively more amplifiers and speakers are used, such as a surround sound mode, and to couple at least one of the amplifiers to a higher power supply voltage in at least one other mode that uses relatively fewer amplifiers and speakers. This has the effect of reducing the per-speaker audio power output in the mode that employs relatively more amplifiers and speakers at lower supply voltage.

15 In carrying out an inventive feature, lowering the per speaker power output in this manner can be used to activate and use relatively more speakers, for example in a more dispersed array, without increasing substantially the total power output from all the speakers that are used. Voltages V1, V2, V3, V4 and Vcc may be produced from a single power supply, not shown, having a fixed maximum power rating. By providing lower voltage levels, when more speakers and amplifiers are energized and higher voltage levels, when fewer speakers and amplifiers are energized, the same fixed maximum power rating can be, advantageously, maintained.

20 For example, when switching from using two speakers to four speakers, and assuming that the original two speakers are among the four speakers to be used, the switching element couples a lower supply voltages to the amplifiers that drive the original two speakers. The switching element optionally can couple or decouple a supply voltage to the amplifiers for the other two speakers to be used, in order to power those amplifiers when they had not previously been powered in the other mode of operation. Alternatively, those added speakers can be coupled to an amplifier that is always powered, but an active signal is only applied in the mode having the added two speakers. In that event, the added speakers' amplifier should be chosen so as to dissipate minimal power unless its input signal is active.

35 The supply voltages to the two original amplifiers are changed when those amplifiers are to be used to power members of a different number of speakers (reduced when switching from a smaller number to a larger number of active channels, or vice versa). In this way, the total audio power output of the speakers in the smaller group can be approximately the same as the total audio power output of the speakers in the larger group, each of which is less forcefully driven. This arrangement conserves power compared to a similar arrangement in which the powers supply voltage to the original speakers is not reduced. The power supply savings accrue even if the amplitude of the input signals to the switched-supply amplifiers is adjusted so as to use the signal amplitude as a means to adjust the volume of the audio output, because there is a smaller

5 voltage drop at least across the output or driver stage of the amplifier, and less power dissipation. As indicated before, by providing lower voltage levels, when more speakers and amplifiers are energized and higher voltage levels, when fewer speakers and amplifiers are energized, the same fixed maximum power rating can be, advantageously, maintained. Therefore, there is no need to provide
10 a power supply with a higher power rating in each of the modes of operation.

A preferred application of the invention is switching from a stereo mode to a surround sound mode, but the same technique could apply to other situations in which a change is made in the number of speakers and amplifiers that are actively employed. In the preferred application the audio system has a main two
15 channel amplifier and associated speakers, and an external two channel amplifier having an audio output coupleable to external speakers. Another application is to an audio system having a main two channel amplifier with an audio output coupleable to front stereo speakers and a surround two channel amplifier having an audio output coupleable to rear stereo speakers. The audio system optionally
20 can have a center channel speaker driven by at least a selectable one of the amplifiers. Typically, the center channel is used to drive both cabinet speakers monaurally in surround sound mode and the front and rear surround sound signals are directed to the front and rear pairs of external speakers.

The audio system 20 as shown in Figure 1 can be a television chassis
25 home entertainment system, containing three stereo audio power amplifiers as shown in Figures 2 and 3, which support different configurations. In a first or internal stereo mode, a 12.5 watt per channel stereo amplifier 54 (i.e., two channel amplifier) is coupled to drive two self contained or cabinet speakers 24, 25. Additionally, a 12.5 watt per channel stereo amplifier 56 is provided for
30 coupling, at the user's choice, to two external speakers 27, 28 that are to be used as front speakers (see also Figure 1). Use of the external speakers can provide a second mode of operation (an external stereo mode) that is comparable to the main internal stereo mode, if the internal speakers are disabled when the external speakers are used. Otherwise, if the user chooses to use the cabinet
35 speakers and the external front speakers at the same time, then the total audio power level might be doubled because two stereo amplifiers would power four speakers, whereas in the internal mode there was one stereo amplifier of the same rated wattage, driving the two cabinet speakers.

A third mode of operation is a five channel surround mode. In this mode,
40 the two internal speakers 24, 25 can carry the center front channel signal. The front external speakers 27, 28 carry the front left and right signals. A third amplifier 52 powers the left and right rear surround speakers 32.

Preferably, the user may choose by appropriate menu selections, switch inputs or the like, to operate in surround mode or in stereo mode or in various

5 combinations of internal and external speaker use. Such a choice might be advantageous even if signals are available for driving the rear speakers 32, either in the program being presented or as a processed version of the front speaker signals. For example, the user may not have wired the system to support surround sound, or if already wired may simply choose to use the system in a
10 less imposing manner than would be possible using all its capabilities.

In a full five channel surround sound mode, taking advantage of front and rear external speakers, and using the two internal (cabinet) speakers 24, 25 for the center speaker signal, it would be possible to power the main internal stereo amplifier 54 and the external front speaker amplifier 56 by their 12.5 watt per
15 channel stereo amplifiers discussed above, using the same nominal supply voltage to power both amplifiers. If the third stereo amplifier 52 was of the same 12.5 watt rated power and was also driven from the nominal supply voltage to power the rear surround speakers, changing from stereo to surround sound modes would increase the acoustic power output by a factor of three.
20 The relative power level of the center channel would be twice the level of any other single channel. This would likely require adjustment of the audio levels. Even assuming an automatic adjustment, the power supply would be effectively over designed for the application.

According to the present inventive approach to this problem, power supply
25 levels to the amplifiers are switched between alternative higher and lower voltages to adjust the relative power outputs of the channels and to reduce power dissipation. As shown in Figure 3, this can be accomplished so as to have the same total audio output power and the same total power requirement from the power supply in the stereo mode as in the surround mode.
30 Furthermore, according to the inventive solution, the power output per channel can be made equal in the surround sound mode for all five channels, and the capacity of the power supply is fully used in both modes.

The main stereo amplifier 54 of Figure 3 (i.e., the internal or cabinet speaker amplifier) is supplied with +34 volts dc, through a saturated bipolar
35 transistor switch Q2. Switch Q2 is conductive or "on" in the stereo mode only, and in that mode couples the +34 volts dc supply voltage, but for a base-emitter voltage drop, to a power supply terminal 111 of the main stereo amplifier 54. Switch Q2 is switched into the stereo mode by an output of a system control network of switching elements 62. The control element can be
40 associated with an audio source that is capable of switching between the stereo and other modes. Preferably the output of the control element is settable at the user's option in association with pre-selecting stereo operation.

Another supply voltage at +16 volts dc is coupled to the power supply terminal of main stereo amplifier 54 through diode D1. Thus diode D1 is reverse

5 biased in the stereo mode and blocks conduction from the + 34 volt supply to the + 16 volt supply.

In the stereo mode, the main stereo amplifier 54 supplies 12.5 watts of audio power per channel to each of the two cabinet mounted internal 8 ohm speakers 24, 25, due to the presence of the + 34 volt supply. The total power
10 output in this stereo mode is 25 watts.

In the surround sound mode, switch Q2 is switched off, decoupling the + 34 volt supply from the main stereo amplifier. Diode D1 becomes forward biased and supplies + 16 volts to the main stereo amplifier, less a diode drop. At this supply voltage, the main stereo amplifier 54 supplies only 2.5 watts per
15 channel or a total of 5 watts. In this mode, the signal input to both parallel amplifiers in the main stereo amplifier 54 preferably is the same monaural signal, namely the center channel signal in the surround sound mode from the audio source.

The external stereo amplifier 56 is supplied + 34 volts through another
20 saturated bipolar transistor switch Q3. Another blocking diode D2 is similarly coupled to an additional dc supply at + 24 volts. When switch Q3 is on (in stereo mode only), + 34 volts is applied to the external stereo amplifier 56, less the base-emitter drop of transistor switch Q3 in saturation. Diode D2 is reverse biased, which prevents conduction from the + 34 volt supply to the + 24 volt
25 supply. The external stereo amplifier 56 supplies 12.5 watts per channel to each external 8 ohm speaker for a total of 25 watts output power in the stereo mode.

Transistor switch Q3 is switched off in the surround sound mode. The + 34 volt supply cannot conduct current to the external stereo amplifier. Diode D2 becomes forward biased and supplies + 24 volts to the voltage supply
30 terminal of the external stereo amplifier 56, which at that supply voltage can supply 5 watts to each channel or a total of 10 watts.

The third amplifier, namely surround amplifier 52, is supplied + 24 volts in this embodiment, which is not switched between voltage levels when changing between modes. The voltage can optionally be switched on and off by
35 additional switch means (not shown), but this amplifier 52 is used only in surround sound mode and need not be switched to accommodate different power levels as is the case with the main and external stereo amplifiers 54, 56. At the noted supply voltage of 24 volts, the surround amplifier 52 produces 5 watts per channel, namely for the left and right rear or surround speakers.

40 According to the foregoing embodiment, the total output power of the amplifiers operating in the foregoing modes is 25 watts. Inasmuch as the power supply voltages are reduced when relatively more amplifier channels and speakers are active, and increased when fewer channels and speakers are active, the invention provides an efficient output level control that also prevents undue

5 power dissipation. Whether the system is in the two channel stereo mode or the five channel surround sound mode, the power supply is fully utilized, and the output power levels in both these modes are the same.

In addition to the basic power supply switching arrangements as discussed, the embodiment of the invention shown in Figure 3 comprises filter
10 capacitors C1, C2 and C3 coupled between the supply voltage terminals of each dual amplifier package 52, 54, 56 and ground for decoupling the amplifiers from variations in the power supply voltage. Additionally, each of the supply voltage inputs to the amplifiers are coupled to a voltage divider to ground, defined by
15 resistors Ra, Rb. The junction of resistors Ra, Rb is coupled to the amplifier bias input, and resistor Rb is coupled in parallel with a capacitor Cb, namely between the bias input and ground. When changing from a lower supply voltage to a higher supply voltage, capacitor Cb charges through resistor Ra, bringing the bias input voltage up smoothly to a reference value equal to one-half of the supply voltage, defined by the voltage divider.

20 Each of dual amplifier package 52, 54 and 56 includes a pair of audio amplifiers, for example, a non-inverting amplifier 54a of amplifier package 54. The gain of amplifier 54a is established by a pair of feedback resistors 201 and 202 in a conventional manner. Resistor 202 is AC-coupled to ground via a capacitor 202. A half supply voltage developed at input terminal Bias is DC
25 coupled to a non-inverting input terminal of amplifier 54a. Because resistor 202 is not DC-coupled to ground, the DC gain of amplifier 54a is unity. The result is that a DC component voltage at an output terminal 204 is equal to one half the supply voltage developed at input terminal Bias. Thereby, a single ended power supply is used for producing an output voltage at terminal 204 having the DC
30 component voltage that is equal to one half the supply voltage.

The respective switching elements, including transistors Q1, Q2, Q3 are off in surround sound mode and on in the stereo mode, and control voltage switching. The switching elements are responsive to a status output of the controller which may be generated as a function of user selection of stereo
35 versus surround sound operation. In addition to the switching elements shown for purpose of illustration, additional switching elements (not shown) can be used, for example, to disable one or another of the modes or amplifiers according to user selections and other factors, for example to permit combinations of internal and external speakers other than the standard combinations described
40 above. For some surround program source types, such as Dolby Pro Logic surround, there is nothing inherent in the program material that would give a unique signature, in which event the selection can be made at the option of the user. On the other hand, a digital source such as AC-3 has this capability of carrying a signal representing

- 5 the mode in which the audio signal is encoded, which could be used to switch automatically between the stereo and surround sound modes.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
22